


ADA-8503

Dual AES/EBU Fan-Out Distribution Amplifier User Manual



Ross Part Number: 8503D-004
Issue: 03

ADA-8503 • Dual AES/EBU Fan-Out Distribution Amplifier User Manual

- Ross Part Number: **8503D-004**
- Document Issue: **03**
- Release Date: December 21, 2005. Printed in Canada.

The information contained in this User Manual is subject to change without notice or obligation.

Copyright


© 2005 Ross Video Limited. All rights reserved.

Contents of this publication may not be reproduced in any form without the written permission of Ross Video Limited. Reproduction or reverse engineering of copyrighted software is prohibited.

Notice

The material in this manual is furnished for informational use only. It is subject to change without notice and should not be construed as a commitment by Ross Video Limited. Ross Video Limited assumes no responsibility or liability for errors or inaccuracies that may appear in this manual.

Trademarks

-  is a registered trademark of Ross Video Limited.
- Ross, ROSS, ROSS®, and MLE are registered trademarks of Ross Video Limited.
- All other product names and any registered and unregistered trademarks mentioned in this manual are used for identification purposes only and remain the exclusive property of their respective owners.

Important Regulatory and Safety Notices

Before using this product and any associated equipment, refer to the “Important Safety Instructions” listed below so as to avoid personnel injury and to prevent product damage.

Products may require specific equipment, and /or installation procedures be carried out to satisfy certain regulatory compliance requirements. Notices have been included in this publication to call attention to these Specific requirements.

Symbol Meanings



This symbol on the equipment refers you to important operating and maintenance (servicing) instructions within the Product Manual Documentation. Failure to heed this information may present a major risk of damage or injury to persons or equipment.



Warning

The symbol with the word “**Warning**” within the equipment manual indicates a potentially hazardous situation, which if not avoided, could result in death or serious injury.



Caution

The symbol with the word “**Caution**” within the equipment manual indicates a potentially hazardous situation, which if not avoided, may result in minor or moderate injury. It may also be used to alert against unsafe practices.



Notice

The symbol with the word “**Notice**” within the equipment manual indicates a situation, which if not avoided, may result in major or minor equipment damage or a situation which could place the equipment in a non-compliant operating state.



ESD

Susceptibility

This symbol is used to alert the user that an electrical or electronic device or assembly is susceptible to damage from an ESD event.

Important Safety Instructions



Caution

This product is intended to be a component product of the RossGear 8000 series frame. Refer to the RossGear 8000 series frame User Manual for important safety instructions regarding the proper installation and safe operation of the frame as well as it’s component products.



Warning

Certain parts of this equipment namely the power supply area still present a safety hazard, with the power switch in the OFF position. To avoid electrical shock, disconnect all A/C power cords from the chassis' rear appliance connectors before servicing this area.



Warning

Service barriers within this product are intended to protect the operator and service personnel from hazardous voltages. For continued safety, replace all barriers after any servicing.

This product contains safety critical parts, which if incorrectly replaced may present a risk of fire or electrical shock. Components contained within the product’s power supplies and power supply area, are not intended to be customer serviced and should be returned to the factory for repair.

To reduce the risk of fire, replacement fuses must be the same type and rating.

Only use attachments/accessories specified by the manufacturer.

EMC Notices

US FCC Part 15

This equipment has been tested and found to comply with the limits for a class A Digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case users will be required to correct the interference at their own expense.



Notice

Changes or modifications to this equipment not expressly approved by Ross Video Ltd. could void the user's authority to operate this equipment.

CANADA

This Class "A" digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de classe "A" est conforme à la norme NMB-003 du Canada.

EUROPE

This equipment is in compliance with the essential requirements and other relevant provisions of **CE Directive 93/68/EEC**.

INTERNATIONAL

This equipment has been tested to **CISPR 22:1997** along with amendments **A1:2000** and **A2:2002** and found to comply with the limits for a Class A Digital device.



Notice

This is a Class A product. In domestic environments this product may cause radio interference in which case the user may have to take adequate measures.

Maintenance/User Serviceable Parts


Routine maintenance to this RossGear product is not required. This product contains no user serviceable parts. If the module does not appear to be working properly, please contact Technical Support using the numbers listed under the "Contact Us" section on the last page of this manual. All RossGear products are covered by a generous 5-year warranty and will be repaired without charge for materials or labor within this period. See the "Warranty and Repair Policy" section in this manual for details.

Environmental Information

The equipment that you purchased required the extraction and use of natural resources for its production. It may contain hazardous substances that could impact health and the environment.

To avoid the potential release of those substances into the environment and to diminish the need for the extraction of natural resources, Ross Video encourages you to use the appropriate take-back systems. These systems will reuse or recycle most of the materials from your end-of-life equipment in an environmentally friendly and health conscious manner.

The crossed-out wheeled bin symbol invites you to use these systems.



If you need more information on the collection, reuse, and recycling systems, please contact your local or regional waste administration.

You can also contact Ross Video for more information on the environmental performances of our products.



Contents

Introduction	1-1
In This Chapter	1-1
A Word of Thanks	1-1
Overview	1-2
Functional Block Diagram	1-2
Features	1-3
Documentation Terms	1-3
Installation and Setup	2-1
In This Chapter	2-1
Static Discharge	2-1
Unpacking	2-1
Channel Mode Setup	2-2
Board Installation	2-2
BNC Labels	2-3
Cable Connections	2-3
LEDs	2-4
Specifications	3-1
In This Chapter	3-1
Technical Specifications	3-2
Service Information	4-1
In This Chapter	4-1
Troubleshooting Checklist	4-1
Warranty and Repair Policy	4-2
Ordering Information	5-1
In This Chapter	5-1
ADA-8503 and Related Products	5-1

Introduction

In This Chapter

This chapter contains the following information sections:

- A Word of Thanks
- Overview
- Functional Block Diagram
- Features
- Documentation Terms

A Word of Thanks

Congratulations on choosing the Ross Video **ADA-8503 Dual AES/EBU Fan-Out Distribution Amplifier**. The ADA-8503 is part of a full line of Digital Products within the RossGear Terminal Equipment family of products, backed by Ross Video's experience in engineering and design expertise since 1974.

You will be pleased at how easily your new ADA-8503 fits into your overall working environment. Equally pleasing is the product quality, reliability and functionality. Thank you for joining the group of worldwide satisfied Ross Video customers!

Should you have a question pertaining to the installation or operation of your ADA-8503, please contact us at the numbers listed on the back cover of this manual. Our technical support staff is always available for consultation, training, or service.

Overview

The RossGear ADA-8503 Dual AES/EBU Fan-Out Distribution Amplifier is designed specifically for use in 75-ohm coaxial (SMPTE 276M or AES-3id) systems. Its flexible configuration makes the ADA-8503 the perfect choice for low cost AES distribution within your facility. By moving an on-board jumper, the ADA-8503 can be set as a single, fan-out distribution amplifier; or as a dual, fan-out amplifier. The single configuration provides one input and eight outputs, while the dual configuration provides the first amplifier with one input and four outputs, and a second amplifier with one input and three outputs.

The ADA-8503 distributes incoming data at 22 to 100kHz sampling rates and provides automatic cable equalization for lengths beyond 610m (2000 ft.). It also has been designed with an AES input signal presence detector and indicator LED's.

The ADA-8503 fits into the Ross 8000A series digital frames, with ten cards in the DFR-8110A (2RU) and four cards in the DFR-8104A (1RU). Designed and manufactured to meet the highest quality broadcast industry standards, the ADA-8503 Utility DA is an ideal, flexible, and cost effective solution for the distribution of AES/EBU signals where reclocking is not required. The ADA-8503 also fits Leitch* 6800 series frames.

The ADA-8503 Dual AES/EBU Fan-Out Distribution Amplifier is part of a growing line of RossGear AES solutions, including distribution, conversion, and monitoring.

Functional Block Diagram




Figure 1. Simplified Block Diagram of ADA-8503 Functions

* Leitch is a trademark of Leitch Technology Corporation

Features

The following features make the ADA-8503 Dual AES/EBU Fan-Out Distribution Amplifier a great choice for your digital audio utility distribution requirements:

- Support for any sampling rate in the 22 kHz to 100 kHz range including 32, 44.1, 48, 64, 88.2 and 96 kHz
- Configurable as either single or dual fan-out AES amplifier
- Signal shaping to provide a clean output signal
- Conformity to AES-3id 1995
- Terminating input 75Ω
- Auto equalization for greater than 610m (2000 ft.) of Belden 8281 cable
- Ten card capacity in the Ross DFR-8110A (2RU) digital rack frame
- Four card capacity in the Ross DFR-8104A (1RU) digital rack frame
- Fits Leitch 6800 series frames
- Visual indication of signal presence
- 5-year transferable warranty

Documentation Terms

The following terms are used throughout this guide:

- “**Frame**” refers to the **DFR-8104A** and **DFR-8110A** frames that house the **ADA-8503** card.
- All references to the **DFR-8104A** and **DFR-8110A** also include the **DFR-8104A-C** and **DFR-8110A-C** versions with the cooling fan option. See the respective User Manuals for details.
- “**Operator**” and “**User**” both refer to the person who uses the **ADA-8503**.
- “**Board**”, “**Card**”, and “**Module**” all refer to the **ADA-8503** board itself, including all components and switches.
- “**System**” and “**Video system**” refers to the mix of interconnected production and terminal equipment in which the **ADA-8503** operates.

Installation and Setup

In This Chapter

This chapter contains the following information sections:

- Static Discharge
- Unpacking
- Channel Mode Setup
- Board Installation
- BNC Labels
- Cable Connections
- Dual Configuration Input and Output Cables
- Single Configuration Input and Output Cables
- LEDs

Static Discharge

Whenever handling the ADA-8503 and other related equipment, please observe all static discharge precautions as described in the following note:



Static discharge can cause serious damage to sensitive semiconductor devices. Avoid handling circuit boards in high static environments such as carpeted areas, and when wearing synthetic fiber clothing. Always exercise proper grounding precautions when working on circuit boards and related equipment.

Unpacking

Unpack each ADA-8503 you received from the shipping container, and check the contents against the packing list to ensure that all items are included. If any items are missing or damaged, contact your sales representative or Ross Video directly.




Figure 2. Jumper Locations

Channel Mode Setup

JP5 and **JP6** configure the function of the card to operate as a single or dual channel amplifier. Use Figure 2, the card labeling, and the following discussion to set up the card.

Dual Channel

Set **JP5** and **JP6** as follows:

- **JP5** — IN2 (default setting).
- **JP6** — IN2 (default setting).

Single Channel

Set **JP5** and **JP6** as follows:

- **JP5** — IN1
- **JP6** — OUT

Board Installation

Use the following steps to install the ADA-8503 in a RossGear 8000 series digital distribution frame:

1. Refer to the User Manual of the RossGear 8000 series frame, to ensure that the frame is properly installed according to instructions. If this module is to be installed in any compatible frame other than a Ross Video product, refer to the frame manufacturer's manual for specific instructions.
2. Please note that heat and power distribution requirements within a frame may dictate specific slot placement of cards. Cards with many heat-producing components should be arranged to avoid areas of excess heat build-up, particularly in frames using convectational cooling.
3. After selecting the desired frame installation slot, hold the ADA-8503 card by the edges and carefully align the card edges with the slots in the frame. Then fully insert the card into the frame until the rear connection plug is properly seated.

BNC Labels

The ADA-8503 is supplied with two BNC labels, one for single amplifier configuration and one for dual amplifier configuration. Affix the supplied BNC label, as per the included instructions, to the BNC area on the rear of the rack frame.

Cable Connections

This section provides instructions for connecting cables to the ADA-8503 when mounted in RossGear 8000 series Digital Products Frames. Connect the input and output cables according to the frame rear panel connections diagram in the following figures and related discussions. The inputs are internally terminated in 75 ohms. It is not necessary to terminate unused outputs.




Figure 3. ADA-8503 BNC Designations for RossGear DFR-8110A (2RU frame)

Dual Configuration Input and Output Cables

AES Inputs

The first AES audio input should be connected to BNC IN on the rear of the frame. The second AES audio input should be connected to BNC 7 on the rear of the frame. Set JP1 and JP2 appropriately.

AES Outputs

The ADA-8503 provides four AES outputs (BNC 1,2,3,and 4) for the first amplifier and three AES outputs (BNC 5,6 and 8) for the second amplifier.

Single Configuration Input and Output Cables

AES Input

The AES audio input should be connected to BNC IN on the rear of the frame. Set JP1 and JP2 appropriately.

AES Outputs

The ADA-8503 provides eight AES outputs (BNC 1 through 8).

LEDs

The front edge of the module has two LED indicators, which show the status of the amplifier. They are described in the following figure and table. The module is operating correctly when the Input Present LED is lit.




Figure 4. ADA-8503 LEDs

Table 1. ADA-8503 LED Status Indicator Descriptions

LED	Reference	Status Description
DA1 Input Present	Green	Indicates presence of an input signal.
DA2 Input Present	Green	Indicates presence of an input signal.

Specifications

In This Chapter

This chapter contains the Technical Specifications table.

Technical Specifications

Table 2. ADA-8503 - Technical Specifications

Category	Parameter	Specification
AES Input	Number of Inputs	1 or 2 (jumper configurable)
	Standards	AES-3id (SMPTE 276M)
	Sampling Rates	All rates in the 22kHz to 100kHz range
	Input Impedance	75Ω
	Connector	BNC
	Input Return Loss	>40dB to 6MHz
	Equalization	>610m (2000 ft.) of Belden 8281
	Input Level	1V p-p nominal
AES Output	Number of Outputs	8 single mode 4+3 dual mode
	Standards	AES-3id (SMPTE 276M)
	Output Impedance	75Ω
	Output Isolation	48dB
	Signal Level	1.0V p-p ±10%
	Rise and Fall Time	30ns Typical
	Output Jitter	<4ns peak @ 48kHz (<24.5mUI)
	Output Return Loss	>48dB (0.1 - MHz)
	Electrical Path Length	24ns @ 48kHz
Environmental	Operating Range	5 °C – 40 °C ambient
Power	Total Consumption	1.5W

Specifications are subject to change without notification.

Service Information

In This Chapter

This chapter contains the following sections:

- Troubleshooting Checklist
- Warranty and Repair Policy

Troubleshooting Checklist

Routine maintenance to this RossGear product is not required. In the event of problems with your ADA-8503, the following basic troubleshooting checklist may help identify the source of the problem. If the module still does not appear to be working properly after checking all possible causes, please contact your Ross Video products distributor, or the Ross Video Technical Support department at the numbers listed under the “Contact Us” section at the end of this manual.

1. **Visual Review** – Performing a quick visual check may reveal many problems, such as connectors not properly seated or loose cables. Check the module, the frame, and any associated peripheral equipment for signs of trouble.
2. **Power Check** – Check the power indicator LED on the distribution frame front panel for the presence of power. If the power LED is not illuminated, verify that the power cable is connected to a power source and that power is available at the power main. Confirm that the power supplies are fully seated in their slots. If the power LED is still not illuminated, replace the power supply with one that is verified to work.
3. **Reseat the Card in the Frame** – Eject the card and reinsert it in the frame.
4. **Check Control Settings** – Refer to the Installation and Operation sections of the manual and verify all user-adjustable component settings.
5. **Input Signal Status** – Verify that source equipment is operating correctly and that a valid signal is being supplied.
6. **Output Signal Path** – Verify that destination equipment is operating correctly and receiving a valid signal.
7. **Module Exchange** – Exchanging a suspect module with a module that is known to be working correctly is an efficient method for localizing problems to individual modules.

Warranty and Repair Policy

The RossGear ADA-8503 is warranted to be free of any defect with respect to performance, quality, reliability, and workmanship for a period of FIVE (5) years from the date of shipment from our factory. In the event that your RossGear ADA-8503 proves to be defective in any way during this warranty period, Ross Video Limited reserves the right to repair or replace this piece of equipment with a unit of equal or superior performance characteristics.

Should you find that this RossGear ADA-8503 has failed after your warranty period has expired, we will repair your defective product should suitable replacement components be available. You, the owner, will bear any labor and/or part costs incurred in the repair or refurbishment of said equipment beyond the FIVE (5) year warranty period.

In no event shall Ross Video Limited be liable for direct, indirect, special, incidental, or consequential damages (including loss of profits) incurred by the use of this product. Implied warranties are expressly limited to the duration of this warranty.

This RossGear ADA-8503 User Manual provides all pertinent information for the safe installation and operation of your RossGear Product. Ross Video policy dictates that all repairs to the RossGear ADA-8503 are to be conducted only by an authorized Ross Video Limited factory representative. Therefore, any unauthorized attempt to repair this product, by anyone other than an authorized Ross Video Limited factory representative, will automatically void the warranty. Please contact Ross Video Technical Support for more information.

In Case of Problems

Should any problem arise with your RossGear ADA-8503, please contact the Ross Video Technical Support Department. (Contact information is supplied at the end of this publication.)

A Return Material Authorization number (RMA) will be issued to you, as well as specific shipping instructions, should you wish our factory to repair your RossGear ADA-8503. If required, a temporary replacement module will be made available at a nominal charge. Any shipping costs incurred will be the responsibility of you, the customer. All products shipped to you from Ross Video Limited will be shipped collect.

The Ross Video Technical Support Department will continue to provide advice on any product manufactured by Ross Video Limited, beyond the warranty period without charge, for the life of the equipment.

Ordering Information

In This Chapter

This chapter contains ordering information for the ADA-8503 and related products.

ADA-8503 and Related Products

Standard Equipment

- **ADA-8503** Dual AES/EBU Fan-Out Distribution Amplifier

Optional Equipment

- **8503D-004** Dual AES/EBU Fan-Out Distribution Amplifier User Manual (additional User Manual)
- **DFR-8104A** Digital Products Frame and Power Supply (PS-8102) (1RU, holds 4 modules, includes 1 power supply)
- **DFR-8104A-C** Digital Products Frame with Cooling Fan Module and Power Supply (PS-8102) (1RU, holds 4 modules, includes 1 power supply)
- **DFR-8110A** Digital Products Frame and Power Supply (PS-8102) (2RU, holds 10 modules, includes 1 power supply)
- **DFR-8110A-C** Digital Products Frame with Cooling Fan Module and Power Supply (PS-8102) (2RU, holds 10 modules, includes 1 power supply)

Your **ADA-8503 Dual AES/EBU Fan-Out Distribution Amplifier** is a part of the RossGear family of products. Ross Video offers a full line of RossGear terminal equipment including distribution, conversion, monitoring, synchronizers, encoders, decoders, keyers, switches, as well as analog audio and video products.

Notes:

Notes:

Contact Us

Contact our friendly and professional support representatives for the following:

- Name and address of your local dealer
- Product information and pricing
- Technical support
- Upcoming trade show information

PHONE	General Business Office and Technical Support	613 • 652 • 4886
	After-hours Support	613 • 349 • 0006
	Fax	613 • 652 • 4425
E-MAIL	General Information	solutions@rossvideo.com
	Technical Support	techsupport@rossvideo.com
POSTAL SERVICE	Ross Video Limited	8 John Street, Iroquois, Ontario, Canada K0E 1K0
	Ross Video Incorporated	P.O. Box 880, Ogdensburg, New York, USA 13669-0880

Visit Us

Please visit us at our website for:

- Company information
- Related products and full product lines
- On-line catalog
- Trade show information
- News
- Testimonials

www.rossvideo.com
