

## AMX AXB-PT30 PosiTrack Camera Controller

### Requirements

- Robotic Camera Interface Software Option
- Serial Interface Cables

### Port Connections

	Switcher		Robotic Camera
Robotic Camera	REMOTE Port (female)	⇒	RS-232 Port
Video	Input BNC	⇒	Video Out BNC

### Pinouts

Switcher	AXB-PT30 PosiTrack
2 (Tx)	2 (Rx)
3 (Rx)	3 (Tx)
5 Ground	5 Ground

### Switcher Setup

#### To Set Up Communications

1. Press **HOME** ⇒ **Setup** ⇒ **Installation** ⇒ **Com Setup** ⇒ **Type**.
  - Use the **Com Port** knob to select the **REMOTE X** port that you connected the AMX AXB-PT30 PosiTrack Camera Controller to.
  - Use the **Device** knob to select **Robotic Cam**.
2. Press **Select Device**.
  - Use the **Device** knob to select **PosiTrack**.
3. Press **Com Type**.
  - Use the **Type** knob to select **RS-232 (RS-232 NULL** on the **Synergy 1**).
4. Press **Com Settings**.
  - Use the **Baud** knob to select **9600**.
  - Use the **Parity** knob to select **NONE**.
5. Press **HOME** ⇒ **Confirm**.

#### To Set Up Video Inputs

1. Press **HOME** ⇒ **Setup** ⇒ **Installation** ⇒ **BNC** ⇒ **BNC Type**.
  - Use the **BNC** knob to select the input BNC that the Video output of the camera being controlled by the AXB-PT30 PosiTrack is connected to.
  - Use the **Type** knob to select **Robotic Cam**.
  - Use the **Video Format** knob to select the video format of the Video output of the camera.
2. Press **More** ⇒ **Camera Setup**.
  - Use the **Controller** knob to select the AXB-PT30 PosiTrack.
  - Use the **Port** knob to select the port that you are using on the AXB-PT30 PosiTrack.
3. Press **Camera Options** and use the knobs to set the options.

Option	Description
Pan Invert	Use the <b>Value</b> knob to invert the direction that the camera moves when using the positioner ( <b>Yes</b> ), or not ( <b>No</b> ).
Tilt Invert	Use the <b>Value</b> knob to invert the direction that the camera moves when using the positioner ( <b>Yes</b> ), or not ( <b>No</b> ).
Zoom Invert	Use the <b>Value</b> knob to invert the direction that the camera zooms when using the positioner ( <b>Yes</b> ), or not ( <b>No</b> ).
Focus Invert	Use the <b>Value</b> knob to invert the focus direction when using the positioner ( <b>Yes</b> ), or not ( <b>No</b> ).
Iris Invert	Use the <b>Value</b> knob to invert the iris direction when using the positioner ( <b>Yes</b> ), or not ( <b>No</b> ).
X Invert	Use the <b>Value</b> knob to invert the direction that the camera moves in the X-axis when using the positioner ( <b>Yes</b> ), or not ( <b>No</b> ).
Y Invert	Use the <b>Value</b> knob to invert the direction that the camera moves in the Y-axis when using the positioner ( <b>Yes</b> ), or not ( <b>No</b> ).
Z Invert	Use the <b>Value</b> knob to invert the direction that the camera moves in the Z-axis when using the positioner ( <b>Yes</b> ), or not ( <b>No</b> ).

4. Press **HOME** ⇒ **Confirm**.

### Device Setup

Ensure the port on the AXB-PT30 PosiTrack that is connected to the switcher is configured for RS-232.



Video Production Technology

4999DR-076-04

## Compatibility

Robotic Camera	Version
AMX AXB-PT30 PosiTrack Camera Controller	--
<b>Switchers</b>	
Synergy 1 SD	--
Synergy Series SD	--
Synergy MD/X	--
Vision MD/X	--
Vision QMD/X	16.0
Vision MultiPanel Support	--
<b>Automation</b>	
OverDrive	12.0
<b>Port Expanders</b>	
BSS4	✓
Comtrol DeviceMaster	✓



Video Production Technology